



© Firetrol, Inc. Not for construction.
Subject to change without notice.

| | | |
|----------------|-----|----------|
| | BY | DD/MM/YY |
| DRAWN BY | ACD | 15/05/23 |
| FINAL APPROVAL | FC | 15/05/23 |

JOCKEY PUMP CONTROLLER ACROSS THE LINE / 3 PHASES

MODEL: FTA570E


BUILT TO THE LATEST EDITION OF THE UL 508A



NYC
Dept of Building
Approved

DRAWING NUMBER
FC570E-003/E
DWG REV. 0
SHEET 1 OF 1

Power Connections and Motor Connections



Line Terminals (L1,L2,L3,GND)

| Maximum Motor Horsepower | | | | | Wire Size Copper Only | Torque | Wire Size Ground Copper Only |
|--------------------------|----------|----------|----------|----------|-----------------------|--------|------------------------------|
| 200-208V | 220-240V | 380-416V | 440-480V | 575-600V | | | |
| 30HP | 30HP | 50HP | 50HP | 50HP | #14 AWG - #1 AWG | 9 Nm | #14 AWG - #2 AWG |

Motor Terminals (T1,T2,T3,GND)

| Maximum Motor Horsepower | | | | | Wire Size Copper Only | Torque | Wire Size Ground Copper Only |
|--------------------------|----------|----------|----------|----------|-----------------------|--------|------------------------------|
| 200-208V | 220-240V | 380-416V | 440-480V | 575-600V | | | |
| 7.5HP | 10HP | 15HP | 20HP | 25HP | #14 AWG - #8 AWG | 5 Nm | #14 AWG - #2 AWG |
| 20HP | 20HP | 30HP | 40HP | 50HP | #14 AWG - #2 AWG | 5 Nm | #12 AWG - #2 AWG |
| 25HP | 30HP | 50HP | 50HP | - | #10 AWG - #1 AWG | 9 Nm | #12 AWG - #2 AWG |