

Electric Fire Pump Controllers - Upstream Disconnecting Means

ELECTRIC FIRE PUMP CONTROLLER UPSTREAM DISCONNECTING MEANS

Example: **FTA990-M100B-xxx**

Controller Model Number

Short Circuit Current Rating

200 - 208V Standard SCCR 5-200 HP - "M" 100kA
220 - 240V Standard SCCR 5-200 HP - "M" 100kA
380 - 415V Standard SCCR 5-300 HP - "M" 65kA
440 - 480V Standard SCCR 5-400 HP - "M" 65kA
600V Standard SCCR 5-75 HP - "M" 20kA 100-150 HP - "M" 25kA 200-300 HP - "M" 30kA 350-450 HP - "M" 42kA

Options -MZN - Neutral Lug, Service Entrance, Non-Insulated, Bonded to Enclosure
--

Three Phase Voltage A - 220-240 Volt, 60 Hertz (230 V) AZ - 220-230 Volt, 50 Hertz B - 440-480 Volt, 60 Hertz (460 V) BZ - 415 Volt, 50 Hertz C - 550-600 Volt, 60 Hertz (575 V) F - 380 Volt, 60 Hertz FZ - 380 Volt, 50 Hertz FF - 400 Volt, 60 Hertz FX - 400 Volt, 50 Hertz H - 208 Volt, 60 Hertz HH - 200 Volt, 60 Hertz
--

Note: Consult factory for HP or SCCR ratings not listed here.

Horsepower Rating	
03 - 3 HP	100 - 100 HP
05 - 5 HP	125 - 125 HP
07 - 7 1/2 HP	150 - 150 HP
10 - 10 HP	200 - 200 HP
15 - 15 HP	250 - 250 HP
20 - 20 HP	300 - 300 HP
25 - 25 HP	350 - 350 HP
30 - 30 HP	400 - 400 HP
40 - 40 HP	450 - 450 HP
50 - 50 HP	
60 - 60 HP	
75 - 75 HP	

Firetrol, Inc.
3412 Apex Peakway
Apex, North Carolina 27502
P +1 919 460 5200
F +1 919 460 5250
www.firetrol.com

While every precaution has been taken to ensure accuracy and completeness herein, Firetrol, Inc. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications and drawings are subject to change without notice. ©2022 Firetrol, Inc., All Rights Reserved.